

NESS MEDI-ALARM



Supplied with one Pendant Transmitter complete with neckchain and wristwatch strap.

SPECIFICATIONS

MEDI-ALARM MAIN UNIT

FRONT PANEL FUNCTIONS	HELP button, CANCEL button
FRONT PANEL INDICATORS	7 segment LED display, Mains On LED, Batt Low LED
AUDIBLE INDICATOR	Built-in beeper with various functions
MONITORING	Built-in digital dialler for optional connection to a central monitoring station
ALARMS REPORTED	Help from main unit, Help from pendant/s, Inactivity alarm, AC Fail, Low battery main unit, Low battery pendant/s, Test calls
POWER SUPPLY	9V AC Plug Pack (supplied)
BACKUP BATTERY	9V Battery (supplied)
DIMENSIONS (h x w x d)	35 x 170 x 275 mm

MEDI-ALARM PENDANT

BATTERY (Supplied)	3V Lithium (sealed)
BATTERY SHELF LIFE (approx.)	5 years
SUPPLIED WITH	Wristwatch strap and neckchain
DIMENSIONS (h x w x d)	46 x 46 x 12 mm

MEDI-ALARM INACTIVITY PIR

MOUNTING HEIGHT	2 – 3m wall or corner mount
COVERAGE	15m x 15m @ 90° Plus Creep Zones
RANGE SELECT	Selectable High/Low
PULSE COUNT	Selectable 1–2 or 3–4
SENSOR	Dual element pyroelectric
VISUAL DISPLAY	Red alarm LED
BATTERY (Supplied)	9V Lithium
STANDBY CURRENT DRAW	< 16µA
DIMENSIONS (h x w x d)	129 x 70 x 58 mm

MEDI-ALARM INACTIVITY REED SWITCH

REED SWITCH	Miniature glass envelope onboard
TAMPER SWITCH	Cover removal protection
BATTERY (Supplied)	3V Lithium
STANDBY CURRENT DRAW	< 16µA
BATTERY LIFE	3 to 5 years depending on usage
DIMENSIONS (h x w x d)	34 x 87 x 23 mm

NESS MEDI-ALARM

The Ness Medi-Alarm is a sophisticated emergency signalling product which provides peace of mind and independence for the elderly or infirm.

The Medi-Alarm has a high speed digital dialler that reports to a central station in Contact ID format.

Use with most Ness radio transmitters such as, Medi-Alarm Pendant Transmitter, Medi-Alarm Inactivity PIR, Ness Mini Radio Reed Switch or any other Ness radio device.

Supplied with plug pack, dialler, battery backup and one waterproof pendant transmitter.

WIRELESS PENDANTS

Medi-Alarm is activated by simply pressing the button on a wireless Pendant Transmitter which can be worn on a chain around the neck, on a key ring or on the wrist using the wristwatch strap. The pendant Transmitter is rugged and fully waterproof to allow the user complete freedom of movement.

Medi-Alarm can be used with 8 Pendant Transmitters, each with a unique user ID when reporting to the monitoring station. The Pendants Transmitters use a long life Lithium battery for many years of reliable service.

INACTIVITY MONITOR

The Inactivity Monitor is a powerful feature commonly used by people living alone. Wireless PIRs or Wireless Reed Switches are used to monitor the user's normal movement through the house. If movement ceases for a pre-programmed interval, Medi-Alarm will sound a warning and then dial the monitoring station.

PILL REMINDER

Medi-Alarm can be programmed to remind the user to take medication at preset intervals, up to 255 hours.

MEDI-ALARM


100-106	Ness Medi-Alarm
---------	-----------------

OPTIONAL TRANSMITTERS

100-665	Ness Medi-Alarm Pendant transmitter
100-663	Ness Medi-Alarm Inactivity PIR
100-662	Ness Medi-Alarm Inactivity Radio Reed Switch

ACCESSORIES

450-125	Optional Mode 3 phone lead with piggyback plug
895-029	Medi-Alarm replacement wristwatch strap
895-022	Medi-Alarm replacement chain for pendant



NESS SECURITY PRODUCTS
Australian Communications Authority
ELECTROMAGNETIC COMPATIBILITY COMPLIANCE

SYDNEY 02 8825 9222
sales@ness.com.au

MELBOURNE 03 9875 6400
nessmelb@ness.com.au

BRISBANE 07 3399 4910
nessbris@ness.com.au

PERTH 08 9328 2511
nessper@ness.com.au

ADELAIDE 08 8277 7255
adelaide@ness.com.au



Security Products

www.ness.com.au



Quality
Endorsed
Company
ISO9001
LIC.No. QEC2074
NSW Head Office only